



调频接收机用LT10.7M□系列陶瓷滤波器

LT10.7M□ Series Of Ceramic Filter For FM Receiver

技术特性 Technical Characteristics

型号 Part Number	3分贝带宽 3dB Band Width (kHz)	20分贝带宽 20dB Band Width (kHz)max	插入损耗 Insertion Loss (dB) max	阻带衰减 Spurious Attenuation (9~12MHz)(dB) min
LT10.7MA5	280±50	650	6	30
LT10.7MS2	230±50	600	6	40
LT10.7MS3	180±40	520	7	40

输入/输出阻抗: 330Ω
Input/Output Impedance: 330Ω

低损耗LT10.7M□A10系列陶瓷滤波器

LT10.7M□A10 Series Of Ceramic Filter (Low-Loss Type)

技术特性 Technical Characteristics

型号 Part Number	3分贝带宽 3dB Band Width (kHz)	20分贝带宽 20dB Band Width (kHz)max	插入损耗 Insertion Loss (dB) max	阻带衰减 Spurious Attenuation (9~12MHz)(dB) min
LT10.7MA5A10	280±50	590	2.5±2.0	30
LT10.7MS2A10	230±50	520	3.0±2.0	35
LT10.7MS3A10	180±40	470	3.5±1.5	35
LT10.7MJA10	150±40	360	4.5±2.0	35

输入/输出阻抗: 330Ω
Input/Output Impedance: 330Ω

宽窄带型LT10.7M□系列陶瓷滤波器

Wide/Narrow Band-width LT10.7M□ Series Of Ceramic Filter

技术特性 Technical Characteristics

型号 Part Number	3分贝带宽 3dB Band Width (kHz)	20分贝带宽 20dB Band Width (kHz)max	插入损耗 Insertion Loss (dB)	阻带衰减 Spurious Attenuation (9~12MHz)(dB) min
LT10.7MA21	400min	950	3.0±2.0	20
LT10.7MA19	±175min	950	3.0±2.0	20
LT10.7MA20	330±50	680	4.0±2.0	30
LT10.7MHY	110±30	350	5.5.0±2.0	30
LT10.7MFP	20min	95	6.0max	24(10.7±1.0MHz)

输入/输出阻抗: 470Ω (A19)、330Ω (A21,A20,HY),600Ω (FP)
Input/Output Impedance: 470Ω (A19)、330Ω (A21,A20,HY),600Ω (FP)